



**BEAMZ**  
**MADE**  
**EAZY**

151.511 V1.1

**BAC552Z**

**QUICK START GUIDE**

# CONTROL MENU

MENU		DESCRIPTION
<b>A001</b>	A001-A512	Press Up or Down to modify address codes (A001-A512), press ENTER to Save
<b>CH10</b>	CH10-CH18	Press Up or Down to modify Channels CH10,CH18, press ENTER to Save
<b>N000</b>	N000-N084	Press Up or Down to choose built-in effects (N000- N084), default N007, press ENTER to Save
<b>S000</b>	S000-S255	Press Up or Down to modify speed (S000- S255), default S024, press ENTER to save
<b>S0UD</b>	Soud	Sound-activated
<b>R000</b>	R000-R255	Press Up or Down to adjust red brightness (R000- R255), press ENTER to save
<b>G000</b>	G000-G255	Press Up or Down to adjust green brightness (G000- G255), press ENTER to save
<b>B000</b>	B000-B255	Press Up or Down to adjust blue brightness (B000- B255), press ENTER to save
<b>W000</b>	W000-W255	Press Up or Down to adjust white brightness (W000- W255), press ENTER to save
<b>M000</b>	M000-M2555	Zoom motor
<b>T000</b>	T000-T100	Display temperature
<b>FACTORY SETTINGS</b>	R032-R255	Press Up or Down to adjust Red LED current (R032-R255), press ENTER to save
	G032-G255	Press Up or Down to adjust Green LED current (G032-G255), press ENTER to save
	B032-B255	Press Up or Down to adjust Blue LED current (B032-B255), press ENTER to save
	W032-W255	Press Up or Down to adjust White LED current (W032-W255), press ENTER to save
	M000-M255	Zoom motor current
	FA-N	Fan set: FA-N Light on indicates the fan is on, FA-Y Starts the fan when it reaches the set temperature protection point, press ENTER to save
	T040-T105	Press Up or Down to set temperature protection point (40°C-105°C), press ENTER to save
Send	Press Up or Down to send factory settings parameters to all other fixtures connected. Confirm sending by pressing the menu button for 3 seconds, otherwise press Confirm to deny the sending.	

# DMX CHANNELS

## 10 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Zoom
2		000-255	Dimmer
3		000-255	Strobe
4		000-255	R Red linear dimming
5		000-255	G Green linear dimming
6		000-255	B Blue linear dimming
7		000-255	W White linear dimming
8		000-255	Mode
9		000-255	Speed
10		000-249	No function
		250-255	Reset all

## 18 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Zoom
2		000-255	Dimmer
3		000-255	Strobe
4		000-255	The first circle of red LED
5		000-255	The first circle of green LED
6		000-255	The first circle of blue LED
7		000-255	The first circle of White LED
8		000-255	The second circle of red LED
9		000-255	The second circle of green LED
10		000-255	The second circle of blue LED
11		000-255	The second circle of White LED
12		000-255	The third circle of red LED
13		000-255	The third circle of green LED
14		000-255	The third circle of blue LED
15		000-255	The third circle of White LED
16		000-255	Mode
17		000-255	Speed
18		000-249	No function
		250-255	Reset all



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

