



153.309 V1.0

BS1200

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
DMX ADDR	A001-A512	DMX address setting
	MODE	
DMX CH	7 / 14 / 21 / 150	DMX channel mode
	AUTO	Pro00-20
SOUND	Sp00-99	Auto program mode
	Pro00-20	Speed auto program
Manual	Sp00-99	Sound program
	Pro00-20	Speed sound program
Dimmer	Dimmer	Master Dimmer 0-100%
	Red	Dimmer Red 0-100%
Green	Green	Dimmer Green 0-100%
	Blue	Dimmer Blue 0-100%
CWhite1	CWhite1	Beam Dimmer White 0-100%
	CWhite2	Dimmer White 0-100%
WWhite2	WWhite2	Dimmer Warm White 0-100%
	W2Cct	Warm White Correlated Colour Temperature
W1-Show	W1-Show	Beam effect
	W1-Sp	Beam effect speed
W1-Str	W1-Str	Strobe
	W2-Show	White/Warm White effect
W2-Sp	W2-Sp	White/Warm White effect speed
	W2-Str	White/Warm White strobe
RGB-Show	RGB-Show	Pixel effect
	RGB-Sp	Pixel speed
RGB-Str	RGB-Str	Pixel strobe
	RGB-BG-R	Background Red
RGB-BG-G	RGB-BG-G	Background Green
	RGB-BG-B	Background Blue
SETTINGS	Display	ON/OFF
	Display Rev	ON/OFF
Dmx Fail	Blackout	When No DMX
	Manual	
Auto	Auto	
	Hold	
Sound Mode	Hold	Sound mode options
	Blackout	
Default	Default	ON/YES
	Firmware	Vxxx
SYSTEM	Time Info	xxxH
	Temp	xx°C

DMX CHANNELS

7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Dimmer Red 0-100%
2	GREEN	000-255	Dimmer Green 0-100%
3	BLUE	000-255	Dimmer Blue 0-100%
4	WHITE	000-255	Dimmer Beam White 0-100%
5	WHITE	000-255	Dimmer White 0-100%
6	WARM WHITE	000-255	Dimmer Warm White 0-100%
7	STOBE	000-255	Strobe from slow to fast

14 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	RED	000-255	Dimmer Red 0-100%
2	GREEN	000-255	Dimmer Green 0-100%
3	BLUE	000-255	Dimmer Blue 0-100%
4	WHITE	000-255	Dimmer Beam White 0-100%
5	WHITE	000-255	Dimmer White 0-100%
6	WARM WHITE	000-255	Dimmer Warm White 0-100%
7	CCT	000-255	Correlated Colour Temperature
8	STOBE	000-255	Strobe from slow to fast
9	BEAM EFFECT	000-007	No Function
		008-027	Effect 1
		028-047	Effect 2
		048-067	Effect 3
			
		208-227	Effect 11
		228-247	Effect 12
		248-255	Effect 13
10	BEAM EFFECT SPEED	000-255	Effect speed channel 9 from slow to fast
11	WHITE / WARM WHITE EFFECT	000-007	No Function
		008-015	Effect 1
		016-023	Effect 2
		024-031	Effect 3
			
		232-239	Effect 29
		240-247	Effect 30
		248-255	Effect 31
12	WHITE / WARM WHITE SPEED	000-255	Effect speed channel 11 from slow to fast
13	PIXEL EFFECT	000-007	No Function
		008-015	Red/Green/Blue Effect 1
		016-023	Red/Green/Blue Effect 2
		024-031	Red/Green/Blue Effect 3
			
		232-239	Red/Green/Blue Effect 29
		240-247	Red/Green/Blue Effect 30
		248-255	Red/Green/Blue Effect 31
14	PIXEL EFFECT SPEED	000-255	Effect speed channel 13 from slow to fast

21 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	MASTER DIMMER	000-255	Master Dimmer 0-100%
2	RED	000-255	Dimmer Red 0-100%
3	GREEN	000-255	Dimmer Green 0-100%
4	BLUE	000-255	Dimmer Blue 0-100%
5	WHITE	000-255	Dimmer Beam White 0-100%
6	WHITE	000-255	Dimmer White 0-100%
7	WARM WHITE	000-255	Dimmer Warm White 0-100%
8	CCT	000-255	Correlated Colour Temperature
9	BEAM EFFECT	000-007	No Function
		008-027	Effect 1
		028-047	Effect 2
		048-067	Effect 3
			
		208-227	Effect 11
		228-247	Effect 12
		248-255	Effect 13
10	BEAM EFFECT SPEED	000-255	Effect speed channel 9 from slow to fast
11	BEAM STROBE	000-255	Strobe from slow to fast
12	WHITE / WARM WHITE EFFECT	000-007	No Function
		008-015	Effect 1
		016-023	Effect 2
		024-031	Effect 3
			
		232-239	Effect 29
		240-247	Effect 30
		248-255	Effect 31
13	WHITE / WARM WHITE SPEED	000-255	Effect speed channel 11 from slow to fast
14	STROBE	000-255	Strobe White/Warm White from slow to fast
15	PIXEL EFFECT	000-007	No Function
		008-015	Red/Green/Blue Effect 1
		016-023	Red/Green/Blue Effect 2
		024-031	Red/Green/Blue Effect 3
			
		232-239	Red/Green/Blue Effect 29
		240-247	Red/Green/Blue Effect 30
		248-255	Red/Green/Blue Effect 31
16	PIXEL EFFECT SPEED	000-255	Effect speed channel 13 from slow to fast
17	STROBE	000-255	Pixel Strobe from slow to fast
18	BACKGROUND RED	000-255	Dimmer Background Red 0-100%
19	BACKGROUND GREEN	000-255	Dimmer Background Green 0-100%
20	BACKGROUND BLUE	000-255	Dimmer Background Blue 0-100%
21	PIXEL FX EFFECT	000-255	Pixel effect movement counter clockwise

150 CHANNELS

CHANNELS	FUNCTION	VALUE	DESCRIPTION
1	PIXEL RED	000-255	Segment 1 Dimmer Red 0-100%
2	PIXEL GREEN	000-255	Segment 1 Dimmer Green 0-100%
3	PIXEL BLUE	000-255	Segment 1 Dimmer Blue 0-100%
4	PIXEL RED	000-255	Segment 2 Dimmer Red 0-100%
5	PIXEL GREEN	000-255	Segment 2 Dimmer Green 0-100%
6	PIXEL BLUE	000-255	Segment 2 Dimmer Blue 0-100%
.....			
58	PIXEL RED	000-255	Segment 20 Dimmer Red 0-100%
59	PIXEL GREEN	000-255	Segment 20 Dimmer Green 0-100%
60	PIXEL BLUE	000-255	Segment 20 Dimmer Blue 0-100%
61	BEAM	000-255	Segment 1 Dimmer White 0-100%
62	BEAM	000-255	Segment 2 Dimmer White 0-100%
63	BEAM	000-255	Segment 3 Dimmer White 0-100%
.....			
69	BEAM	000-255	Segment 9 Dimmer White 0-100%
70	BEAM	000-255	Segment 10 Dimmer White 0-100%
71	WHITE	000-255	Segment 1 Dimmer White 0-100%
72	WARM WHITE	000-255	Segment 1 Dimmer Warm White 0-100%
73	WHITE	000-255	Segment 2 Dimmer White 0-100%
74	WARM WHITE	000-255	Segment 2 Dimmer Warm White 0-100%
.....			
147	WHITE	000-255	Segment 39 Dimmer White 0-100%
148	WARM WHITE	000-255	Segment 39 Dimmer Warm White 0-100%
149	WHITE	000-255	Segment 40 Dimmer White 0-100%
150	WARM WHITE	000-255	Segment 40 Dimmer Warm White 0-100%







BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.



BEAMZLIGHTING.COM