



BEAMZ
MADE
EAZY

150.706 V1.1

LCB144 MKII

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
ADDR	A001-A512	Set DMX address
CHND	3CH	3 Channels DMX mode
	4CH	4 Channels DMX mode
	7CH	7 Channels DMX mode
	24CH	24 Channels DMX mode
	28CH	28 Channels DMX mode
SLAV	SL01-SL04	Slave mode
AUTO	Pr-0	Chase 1-8 auto running
	Pr-1-Pr-8	Chase 1-8
	Pr-9	Gradual change
SOUN	S-1 -	Sound mode 1
	S--2	Sound mode 2
NANU	r000-r255	Manual red 0-100%
	G000-G255	Manual green 0-100%
	b000-b255	Manual blue 0-100%
LED	ON	Display always on
	OFF	Display will turn off after 30 seconds
DISP	NO	Display normal
	YES	Display invert
VER		Software version

DMX CHANNELS

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	Master dimmer	000-255	Master dimmer 0-100%

7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	Master dimmer	000-255	Master dimmer 0-100%
5	Strobe	000-255	Strobe speed
6	Chase	000-025	Chase mode 0 (chase 1-8 cycle running)
		026-051	Chase mode 1
		052-077	Chase mode 2
		078-103	Chase mode 3
		104-129	Chase mode 4
		130-155	Chase mode 5
		156-181	Chase mode 6
		182-207	Chase mode 7
		208-233	Chase mode 8
		234-255	Chase mode 9
7	Mode	000	Dimmer mode (custom control)
		001-013	Chase mode (Selection by channel 6)
		014-027	Sound mode A0 (all mode A cycle running)
		028-139	Sound mode A1-A8 alone
		140-153	Sound mode B0 (all mode B cycle running)
		154-255	Sound mode B1-B8 alone

24 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Section 1	000-255	Red dimmer 0-100%
2	Colour	000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	Section 2	000-255	Red dimmer 0-100%
5	Colour	000-255	Green dimmer 0-100%
6		000-255	Blue dimmer 0-100%
7	Section 3	000-255	Red dimmer 0-100%
8	Colour	000-255	Green dimmer 0-100%
9		000-255	Blue dimmer 0-100%
10	Section 4	000-255	Red dimmer 0-100%
11	Colour	000-255	Green dimmer 0-100%
12		000-255	Blue dimmer 0-100%
13	Section 5	000-255	Red dimmer 0-100%
14	Colour	000-255	Green dimmer 0-100%
15		000-255	Blue dimmer 0-100%
16	Section 6	000-255	Red dimmer 0-100%
17	Colour	000-255	Green dimmer 0-100%
18		000-255	Blue dimmer 0-100%
19	Section 7	000-255	Red dimmer 0-100%
20	Colour	000-255	Green dimmer 0-100%
21		000-255	Blue dimmer 0-100%
22	Section 8	000-255	Red dimmer 0-100%
23	Colour	000-255	Green dimmer 0-100%
24		000-255	Blue dimmer 0-100%



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!





150.036 

AC-425 Soft case

The **AC-425 Soft Case** is newly designed to protect and extend the life of speaker and lighting stands. Its wide opening allows for a variety of fixtures to fit inside and gear to be removed quickly and easily. It fits other products and accessories as well. Suitable for mobile DJs, Karaoke rigs and working bands.

Product colour : Black

Dimensions: Internal : 42.5 x 6.25 x 6 inch // 1080 x 159 x 152mm

Weight (kg) : 1,15

- Quality protection for speaker and lighting stands
- For storing extra Lamps, Clamps, Cables and other Accessories
- Saves valuable transport space by allowing fixtures to be stacked without having to be boxed
- Secure view windows make it easy to identify specific fixtures even after they have been packed
- Affordable padded soft case