



**BEAMZ**  
**MADE**  
**EAZY**

150.224 V1.0

**LCB288**

**QUICK START GUIDE**

# CONTROL MENU

MENU			DESCRIPTION	
<b>AUTO</b>	Spl-10		Auto speed 1-10 (slow-fast)	
	St0-9		Strobe speed 0-9 (slow-fast)	
<b>ADDR</b>	6CH	A001-A507	Each channel mode is a separate address, plugged into the console, automatically enter DMX mode	
	9CH	A001-A504		
	12CH	A001-A501		
	32CH	A001-A481		
	64CH	A001-A449		
<b>SHOU</b>	Sh1-12		Program show 1-12	
	Spl-10		Program speed 1-10 (slow -fast)	
	St0-9		Program flash 0-9 (slow -fast)	
<b>SOUD</b>	Sou 1-4		Sound active modes 1-4, sound sensitivity 1-9	
	Sen 1-9			
<b>SLAV</b>	Slave		Slave( Slave, automatically identify the master)	
<b>COLO</b>	R000-255		Red (0-100%) Red dimming	
	G000-255		Green (0-100%) Green dimming	
	B000-255		Blue (0-100%) Blue dimming	
	U000-255		White (0-100%) White dimming	
	St0-9		LED Strobe (slow-fast)	
<b>STAT</b>	CL01-CL37		Static color	
	St0-9		LED strobe (slow-fast)	
<b>SET</b>	dis	10s 20s 30s 60s on	Blacklight shutoff time, from 10s to always on	
	TenP	50-65 °C	Protecting temperature settings, protection within the range of 50-65°C, exceeding this range begins to reduce output power	
	dir	--->		Chasing direction: right
		<---		Chasing direction: left
	Send	yes		Send one-click settings, and the channel mode of all lamps is the channel mode of the current master
	<b>INFO</b>	ver	VVxx	Current software version
		tenp	XXC	The current light plate temperature (degrees Celsius), if the temperature detection line fails, the boot prompt-RT, the menu displays ERROR

# DMX CHANNELS

## 6 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer
2	Strobe	000-009	No function
		010-255	Slow- fast
3		000-255	All Red (0-100%)
4		000-255	All Green (0-100%)
5		000-255	All Blue (0-100%)
6		000-255	All White (0-100%)

## 9 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer
2		000-255	All Red (0-100%)
3		000-255	All Green (0-100%)
4		000-255	All Blue (0-100%)
5		000-255	All White (0-100%)
6	Strobe	000-009	No function
		010-255	Slow- fast
7	5050 RGB Effect Channel	000-005	CH2-4 No Function
		006-011	Pattern effect 1 (CH2-4 controls the pattern color)
		012-017	Pattern effect 2 (CH2-4 controls the pattern color)
		...	...
		222-227	Pattern effect 37 (CH2-4 controls the pattern color)
		228-233	Auto effect (Circle running pattern effect 1-37, CH2-4 controls the pattern color)
		234-236	Sound 1 (CH8 is invalid)
		237-239	Sound 2 (CH8 is invalid)
		240-242	Sound 3 (CH8 is invalid)
		243-255	Sound 4 (CH8 is invalid)
8	5730-W Effect Channel	000-006	CH5 No function
		007-013	Effect 1
		014-020	Effect 2
		...	...
		224-230	Effect 32
		231-255	Auto effect (Circle running pattern effect 1-32)
9		000-255	DMX program speed (slow-fast)

## 12 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer
2		000-255	All Red (0-100%)
3		000-255	All Green (0-100%)
4		000-255	All Blue (0-100%)
5		000-255	All White (0-100%)
6	Strobe	000-009	No function
		010-255	Slow- fast
7		000-255	Background color red dimming in the effect mode (0-100%)
8		000-255	Background color green dimming in the effect mode (0-100%)
9		000-255	Background color blue dimming in the effect mode (0-100%)
10	5050RGB Effect Channel	000-005	CH2-4 No function
		006-011	Pattern effect 1 (CH2-4 controls the pattern color, CH7-9 controls background color)
		012-017	Pattern effect 2 (CH2-4 controls the pattern color, CH7-9 controls background color)
		...	...
		222-227	Pattern effect 37 (CH2-4 controls the pattern color, CH7-9 controls background color)
		228-233	Auto effect (Circle running pattern effect 1-37, CH2-4 controls the pattern color, CH7-9 controls background color)
		234-236	Sound 1 (CH11 is invalid)
		237-239	Sound 2 (CH11 is invalid)
		240-242	Sound 3 (CH11 is invalid)
		243-255	Sound 4 (CH11 is invalid)
11	5730-W Effect Channel	000-006	CH5 No function
		007-013	Effect 1
		014-020	Effect 2
		...	...
		224-230	Effect 32
		231-255	Auto effect (Circle running pattern effect 1-32)
12		000-255	DMX program speed (slow-fast)

### 32 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	RGB 1 Red (0-100%)
2		000-255	RGB 1 Green (0-100%)
3		000-255	RGB 1 Blue (0-100%)
4		000-255	RGB 2 Red (0-100%)
5		000-255	RGB 2 Green (0-100%)
6		000-255	RGB 2 Blue (0-100%)
...		...	...
22		000-255	RGB 8 Red (0-100%)
23		000-255	RGB 8 Green (0-100%)
24		000-255	RGB 8 Blue (0-100%)
25		000-255	W 1 (0-100%)
26		000-255	W 2 (0-100%)
27		000-255	W 3 (0-100%)
28		000-255	W 4 (0-100%)
29		000-255	W 5 (0-100%)
30		000-255	W 6 (0-100%)
31		000-255	W 7 (0-100%)
32		000-255	W 8 (0-100%)

### 64 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	RGB 1 Red (0-100%)
2		000-255	RGB 1 Green (0-100%)
3		000-255	RGB 1 Blue (0-100%)
4		000-255	RGB 2 Red (0-100%)
5		000-255	RGB 2 Green (0-100%)
6		000-255	RGB 2 Blue (0-100%)
...		...	...
46		000-255	RGB 16 Red (0-100%)
47		000-255	RGB 16 Green (0-100%)
48		000-255	RGB 16 Blue (0-100%)
49		000-255	W 1 (0-100%)
...		...	...
64		000-255	W 16 (0-100%)



A series of horizontal dotted lines for writing, spanning the width of the page.





A series of horizontal dotted lines for writing, spanning the width of the page.



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.





150.036 

## AC-425 Soft case

The **AC-425 Soft Case** is newly designed to protect and extend the life of speaker and lighting stands. Its wide opening allows for a variety of fixtures to fit inside and gear to be removed quickly and easily. It fits other products and accessories as well. Suitable for mobile DJs, Karaoke rigs and working bands.

Product colour : Black

Dimensions: Internal : 42.5 x 6.25 x 6 inch // 1080 x 159 x 152mm

Weight (kg) : 1,15

- Quality protection for speaker and lighting stands
- For storing extra Lamps, Clamps, Cables and other Accessories
- Saves valuable transport space by allowing fixtures to be stacked without having to be boxed
- Secure view windows make it easy to identify specific fixtures even after they have been packed
- Affordable padded soft case



177.906 **RL CONNEX**

## CX100-6 DMX Cable XLR Male - XLR Female 6m

PD Connex professional HQ 6 meter DMX signal cable. This flexible signal cable is fitted with high quality XLR connectors and guarantees a trouble-free and reliable DMX signal transmission. Supplied including cable tie.

IP rating : N/A  
Select both plugs : 3-pin XLR (M), 3-pin XLR (F)  
Lead length : 6m  
Conductor : 28x0.1mm  
Outer diameter : 6mm  
Shielding : 60x0.1mm  
Impedance : 120 Ohm  
Weight (kg) : 0,30

- Professional flexible cable
- High quality metal connectors
- Cable tie included
- Various lengths available