



BEAMZ
MADE
EAZY

150.435 V1.0

COBRA WASH100

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
ADDR	A001-A512		DMX address
SET	nodE	dnh	DMX mode
		Ato 1	Auto running mode 1
		Ato 2	Auto running mode 2
		Son	Sound control mode
	Plnt	oFF	Pan forward move
		on	Pan reverse move
	tlnt	oFF	Tilt forward move
		on	Tilt reverse move
REST			Reset
CHND	CH19		DMX channel
CAL	PA S	C000-C255	Pan zero calibration
	PA E	C000-C255	Pan position calibration
	ti S	C000-C255	Tilt zero calibration
	ti E	C000-C255	Tilt position calibration
	SEnS	C000-C100	Sound sensitive

DMX CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	PAN	000-255	0-540 degree move
2	PAN FINE	000-255	16bit adjust
3	TILT	000-255	0-205 degree move
4	TILT FINE	000-255	16bit adjust
5	DIMMER	000-255	0-100% linear dimmer from dark to brighter
6	STROBE	000-003	OFF
		004-103	Synchronous Strobe from slow to fast
		104-107	ON
		108-207	Divide Strobe from slow to fast
		208-212	ON
		213-251	Random strobe from fast to slow
		252-255	ON
		7	WARM WHITE
8	COLD WHITE	000-255	Cold White linear dimmer from dark to brighter
9	COLOR TEMPERATURE	000-009	No Function
		010-255	Cold White to Warm White
10	HALO DIMMER	000-255	0-100% linear dimmer from dark to brighter
11	HALO STROBE	000-004	No Function
		005-250	Synchronous strobe from slow to fast
		251-255	No Function
12	HALO RED	000-255	Red linear dimmer from dark to brighter
13	HALO GREEN	000-255	Green linear dimmer from dark to brighter
14	HALO BLUE	000-255	Blue linear dimmer from dark to brighter
15	HALO COLOR	000-085	Red linear dimmer from brighter to dark, meanwhile, Green linear dimmer from dark to brighter
		086-170	Green linear dimmer from brighter to dark, meanwhile, Blue linear dimmer from dark to brighter
		171-255	Blue linear dimmer from brighter to dark, meanwhile, Red linear dimmer from dark to brighter
16	HALO EFFECT	000-004	No Function
		005-255	Halo Effects(Every 5 Values one effect)
17	HALO EFFECT SPEED	000-127	Clockwise water-flow effect from slow to fast
		128-255	Counterclockwise water-flow effect from slow to fast
18	PT SPEED	000-255	Speed from fast to slow
19	RESET	000-249	No Function
		250-255	All reset after 5s



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.





150.024 

AC-131 Soft case

The **AC-131 Soft Case** is primarily designed to protect and extend the life of mobile lighting fixtures. Its wide opening allows for a variety of fixtures to fit inside and gear to be removed quickly and easily. It fits other products and accessories as well. Suitable for mobile DJs, Karaoke rigs and working bands.

Product colour : Black
Dimensions: Internal : 21 x 8.5 x 13 inch // 530 x 215 x 330mm
Weight (kg) : 0,70

- Quality protection for mobile lighting fixtures
- For storing extra Lamps, Clamps, Cables and other Accessories
- Saves valuable transport space by allowing fixtures to be stacked without having to be boxed
- Secure view windows make it easy to identify specific fixtures even after they have been packed
- Affordable padded soft case



177.906 **RL CONNEX**

CX100-6 DMX Cable XLR Male - XLR Female 6m

PD Connex professional HQ 6 meter DMX signal cable. This flexible signal cable is fitted with high quality XLR connectors and guarantees a trouble-free and reliable DMX signal transmission. Supplied including cable tie.

IP rating : N/A
Select both plugs : 3-pin XLR (M), 3-pin XLR (F)
Lead length : 6m
Conductor : 28x0.1mm
Outer diameter : 6mm
Shielding : 60x0.1mm
Impedance : 120 Ohm
Weight (kg) : 0,30

- Professional flexible cable
- High quality metal connectors
- Cable tie included
- Various lengths available