



BEAMZ
MADE
EAZY

156.100 V1.1

BPL410

QUICK START GUIDE

CONTROL MENU

MENU	MENU 2	MENU 3	MENU 4	
CHOOSE PATTERN	1.Static	(Color)	(Dimming)	
		LED-1	0-255	
		LED-2	0-255	
		LED-3	0-255	
		LED-4	0-255	
		STROBE	0-20	
	2.Macro	1-16		
	3.Show			(Speed)
		AUTO		0-20
		FADE		0-20
		SNAP		0-20
		L1-STRO		0-20
		L2-STRO		0-20
		L3-STRO		0-20
	4.Sound			(Sensitivity)
		SOUND1		0-100
		SOUND2		0-100
SOUND3			0-100	
USER SETTINGS	1.Channel	(Options)		
		004/008		
	2.DMX512	(Address)		
		001-512		
3.Slave	(Mode)			
	OK			
4.WiFi	WiFi Icon			
SYSTEM SETTINGS	1.White Balance	(Color)	(Brightness)	
		LED-1	127-255	
		LED-2	127-255	
		LED-3	127-255	
		LED-4	127-255	
	2.Show Battery Icon	YES/NO		
	3.Display Sleep	ON/15Sec/30Sec/60Sec		
	4.Autolock	ON/OFF		Password [Up Down Up Down Enter]
	5.Infrared Setting	ON/OFF		
	6.Wireless Setting	ON/OFF		
	7.Factory Reset	Password [Up Down Up Down]		
	INFORMATION	1.WORK	(Hours)	001-999
		2.SOFT	(Version)	V.xxx
3.BATT		(Percent)	10-100	

DMX CHANNELS

4 CHANNELS

CHANNEL	VALUE	DESCRIPTION
1	000-255	LED1 from darkness to brightness
2	000-255	LED2 from darkness to brightness
3	000-255	LED3 from darkness to brightness
4	000-255	LED4 from darkness to brightness

8 CHANNELS

CHANNEL	VALUE	DESCRIPTION
1	000-255	Total dimmer ,from dark to bright
2	000-009	Strobe close
	010-255	Strobe open, from slow to fast
3	000-255	LED1 from darkness to brightness
4	000-255	LED2 from darkness to brightness
5	000-255	LED3 from darkness to brightness
6	000-255	LED4 from darkness to brightness
7	000-009	No function
	010-029	Led Selection: CH8 select Led
	030-049	Jump change: CH8 control speed
	050-069	Gradual change: CH8 control speed
	070-089	Pulse change: CH8 control speed
	090-109	LED1 Strobe: CH8 control speed
	110-129	LED2 Strobe: CH8 control speed
	130-149	LED3 Strobe: CH8 control speed
	150-169	LED4 Strobe: CH8 control speed
	170-189	All LED Strobe: CH8 control speed
	190-209	Sound1
	210-229	Sound2
	230-255	Sound3
8	000-255	Select Led; CH7 speed control, from slow to fast; Sound Sensitivity from weak to strong



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.





156.101 **beamZ** Pro

FC410 Flightcase for 2pcs BPL410

The FC410 Flightcase is the perfect solution for safely transporting 2 pieces of BPL410 battery mast lights. This durable road case with easily handles is the perfect solution for mobile use. This case holds up to 2 fixtures with enough space for all power cables and brackets.

Product colour : Black
Material thickness - 0mm : 9mm
Dimensions (L x W x H) : 1200 x 600 x 380mm
Weight (kg) : 15,00

- Sturdy flightcase
- Designed to fit 2 pieces of BPL410 battery mast lights
- 2 Separated compartments inside
- Butterfly locks and aluminium profiles all around
- Ball corners and recessed handles
- Provided with tailor-made solid foam on the inside