



BEAMZ
MADE
EAZY

152.829 V1.0

HYADEN

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
ADDRESS	Addr	001-512	DMX address setting
DMX MODE	Chnd	10 Channels	DMX channel setting
		23 Channels	
MASTER-SLAVE	SInd		NAST
			SL1
MODE	Lost		Blac
			Auto
			Sound
SENSOR	Sens		000-099
LED	Led		ON
			OFF
DISPLAY	Disp	Normal	Normal
		Flip	Flip
MANUAL OPERATION	Naun	000-255	RED
		000-255	GREEN
		000-255	BIUE
		000-255	WHITE
		000-255	LASE
		000-255	PAN
		000-255	DIM
		000-255	STRO
TEST	Test		TEST
SOFTWARE	Ver		V1.0
DEFAULT	Defa		Default
RESET	Rset		Reset

DMX CHANNELS

10 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimmer 0-100%
		000-030	Strobe open
		031-090	Variable strobe slow to fast
		091-105	Strobe open
2	STROBE	106-165	Pulse effect slow to fast
		166-180	Strobe open
		181-240	Random strobe slow to fast
		241-255	Strobe open
		3	PAN
4	LASER EFFECT	000-015	No function
		016-039	Laser effect 1
		040-063	Laser effect 2
		064-087	Laser effect 3
		088-111	Laser effect 4
		112-135	Laser effect 5
		136-159	Laser effect 6
		160-183	Laser effect 7
		184-207	Laser effect 8
		208-231	Laser effect 9
232-255	Laser effect 10		
5	LASER EFFECT SPEED	000-255	Laser effect speed 0-100%
		000-015	Led effect 1
		016-020	Led effect 2
		021-025	Led effect 3
		026-030	Led effect 4
		031-035	Led effect 5
		036-040	Led effect 6
		041-045	Led effect 7
		046-051	Led effect 8
		052-055	Led effect 9
		056-060	Led effect 10
		061-065	Led effect 11
		066-070	Led effect 12
		071-075	Led effect 13
		076-080	Led effect 14
		081-085	Led effect 15
		6	LED EFFECT
091-095	Led effect 17		
096-100	Led effect 18		
101-105	Led effect 19		
106-110	Led effect 20		
111-115	Led effect 21		
116-120	Led effect 22		
121-125	Led effect 23		
126-130	Led effect 24		
131-135	Led effect 25		
136-140	Led effect 26		
141-145	Led effect 27		

		146-150	Led effect 28
		151-155	Led effect 29
		156-160	Led effect 30
		161-165	Led effect 31
		166-170	Led effect 32
		171-180	Led effect 33
		181-185	Led effect 34
		186-190	Led effect 35
		191-195	Led effect 36
		196-200	Led effect 37
		201-205	Led effect 38
		506-210	Led effect 39
		211-215	Led effect 40
		216-222	Led effect colour mix
		223-229	Led effect colour mix
		230-236	Led effect colour mix
		237-243	Led effect colour mix
		244-250	Led effect colour mix
		251-255	Led effect colour mix
7	LED EFFECT SPEED	000-255	Led effect speed 0-100%
8	LASER 1-8	000-239	Laser 1-8 OFF
		240-255	Laser 1-8 ON
9	LED 1-7 MACRO	000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
		106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
10	RESET	000-250	No function
		251-255	Reset ALL

23 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimmer 0-100%
		000-030	Strobe open
		031-090	Variable strobe slow to fast
2	STROBE	091-105	Strobe open
		106-165	Pulse effect slow to fast
		166-180	Strobe open
		181-240	Random strobe slow to fast
		241-255	Strobe open
		3	PAN
4	LASER EFFECT	000-015	No function
		016-039	Laser effect 1
		040-063	Laser effect 2
		064-087	Laser effect 3
		088-111	Laser effect 4
		112-135	Laser effect 5
		136-159	Laser effect 6
		160-183	Laser effect 7
		184-207	Laser effect 8
		208-231	Laser effect 9
5	LASER EFFECT SPEED	232-255	Laser effect 10
		000-255	Laser effect speed 0-100%
		000-015	Led effect 1
		016-020	Led effect 2
		021-025	Led effect 3
		026-030	Led effect 4
		031-035	Led effect 5
		036-040	Led effect 6
		041-045	Led effect 7
		046-051	Led effect 8
		052-055	Led effect 9
		056-060	Led effect 10
		061-065	Led effect 11
		066-070	Led effect 12
		071-075	Led effect 13
		076-080	Led effect 14
		081-085	Led effect 15
		086-090	Led effect 16
		091-095	Led effect 17
		096-100	Led effect 18
		101-105	Led effect 19
		106-110	Led effect 20
		111-115	Led effect 21
		116-120	Led effect 22
		121-125	Led effect 23
		126-130	Led effect 24
		131-135	Led effect 25
		136-140	Led effect 26
		141-145	Led effect 27
146-150	Led effect 28		
151-155	Led effect 29		
6	LED EFFECT	151-155	Led effect 29

		156-160	Led effect 30
		161-165	Led effect 31
		166-170	Led effect 32
		171-180	Led effect 33
		181-185	Led effect 34
		186-190	Led effect 35
		191-195	Led effect 36
		196-200	Led effect 37
		201-205	Led effect 38
		506-210	Led effect 39
		211-215	Led effect 40
		216-222	Led effect colour mix
		223-229	Led effect colour mix
		230-236	Led effect colour mix
		237-243	Led effect colour mix
		244-250	Led effect colour mix
		251-255	Led effect colour mix
7	LED EFFECT SPEED	000-255	Led effect speed 0-100%
8	LASER 1	000-239	Laser 1 OFF
		240-255	Laser 1 ON
9	LASER 2	000-239	Laser 2 OFF
		240-255	Laser 2 ON
10	LASER 3	000-239	Laser 3 OFF
		240-255	Laser 3 ON
11	LASER 4	000-239	Laser 4 OFF
		240-255	Laser 4 ON
12	LASER 5	000-239	Laser 5 OFF
		240-255	Laser 5 ON
13	LASER 6	000-239	Laser 6 OFF
		240-255	Laser 6 ON
14	LASER 7	000-239	Laser 7 OFF
		240-255	Laser 7 ON
15	LASER 8	000-239	Laser 8 OFF
		240-255	Laser 8 ON
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
16	LED 1	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
17	LED 2	106-135	White
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
18	LED 3	000-015	No function

		016-045	Red
		046-075	Green
		076-105	Blue
		106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
19	LED 4	016-045	Red
		046-075	Green
		076-105	Blue
		106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
20	LED 5	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
21	LED 6	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
22	LED 7	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
23	RESET	000-250	No function
		251-255	Reset all



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.





150.036 

AC-425 Soft case

The **AC-425 Soft Case** is newly designed to protect and extend the life of speaker and lighting stands. Its wide opening allows for a variety of fixtures to fit inside and gear to be removed quickly and easily. It fits other products and accessories as well. Suitable for mobile DJs, Karaoke rigs and working bands.

Product colour : Black

Dimensions: Internal : 42.5 x 6.25 x 6 inch // 1080 x 159 x 152mm

Weight (kg) : 1,15

- Quality protection for speaker and lighting stands
- For storing extra Lamps, Clamps, Cables and other Accessories
- Saves valuable transport space by allowing fixtures to be stacked without having to be boxed
- Secure view windows make it easy to identify specific fixtures even after they have been packed
- Affordable padded soft case