



PA amplifier from Fonestar with USB/SD/MP3 recorder/player. It features 4 selectable loudspeaker zones with independent volume control, Phantom power and Priority paging.

Features

- > Power: 360 W maximum, 240 W RMS
- > Response: 80-16,000 Hz \pm 3 dB
- > Distortion: Harmonic: < 1 percent at 1 kHz
- Inputs:**
- > 4 balanced mics/lines, combo (XLR and 6.3 mm jack) 600 Ohms 2 mV and 47,000 Ohms 150 mV, switchable
- > 1 aux, 2 x RCA 47,000 Ohms 300 mV
- > 1 amp in, RCA 10,000 Ohms 1 V
- > 1 tel. input, screw terminals 600 Ohms 100 mV
- Outputs:**
- > 1 line out, 2 x RCA 47,000 Ohms 1V
- > 1 pre out, RCA 600 Ohms 1 V
- > 1 monitor, screw terminals 600 Ohms, 775 mV and 1 W 8 Ohms (aux. input)
- Controls:**
- > Bass: \pm 10 dB
- > Treble: \pm 10 dB
- > Volume: Inputs 1-4, aux, general volume and USB/SD/MP3 player
- > Player: USB/SD/MP3 recorder/player
- > Phantom: 24 V in mics. 1 to 4, selectable
- > Priority: Tel. input and mic. 1 depending on signal level, selectable
- > Zone Selector: 4 selectable loudspeaker zones with independent volume control, maximum 120 W per zone
- > Impedance: 4 Ohms and 100, 70 and 25 V lines, screw terminals

Specifications

- > Power Supply: 230/115 V AC, 600 W and 24 V DC, 312 W
- > Dimensions: 420 x 89 x 300 mm depth, 2 U 19" rack
- > Weight: 11.7 kg
- > MPN: MA-245GU