



BEAMZ
MADE
EAZY

150.706 V1.1

LCB144 MKII

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
ADDR	A001-A512	Set DMX address
CHND	3CH	3 Channels DMX mode
	4CH	4 Channels DMX mode
	7CH	7 Channels DMX mode
	24CH	24 Channels DMX mode
	28CH	28 Channels DMX mode
SLAV	SL01-SL04	Slave mode
AUTO	Pr-0	Chase 1-8 auto running
	Pr-1-Pr-8	Chase 1-8
	Pr-9	Gradual change
SOUN	S-1-	Sound mode 1
	S--2	Sound mode 2
NANU	r000-r255	Manual red 0-100%
	G000-G255	Manual green 0-100%
	b000-b255	Manual blue 0-100%
LED	ON	Display always on
	OFF	Display will turn off after 30 seconds
DISP	NO	Display normal
	YES	Display invert
VER		Software version

DMX CHANNELS

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	Master dimmer	000-255	Master dimmer 0-100%

7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Colour	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	Master dimmer	000-255	Master dimmer 0-100%
5	Strobe	000-255	Strobe speed
6	Chase	000-025	Chase mode 0 (chase 1-8 cycle running)
		026-051	Chase mode 1
		052-077	Chase mode 2
		078-103	Chase mode 3
		104-129	Chase mode 4
		130-155	Chase mode 5
		156-181	Chase mode 6
		182-207	Chase mode 7
		208-233	Chase mode 8
		234-255	Chase mode 9
7	Mode	000	Dimmer mode (custom control)
		001-013	Chase mode (Selection by channel 6)
		014-027	Sound mode A0 (all mode A cycle running)
		028-139	Sound mode A1-A8 alone
		140-153	Sound mode B0 (all mode B cycle running)
		154-255	Sound mode B1-B8 alone

24 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Section 1	000-255	Red dimmer 0-100%
2	Colour	000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	Section 2	000-255	Red dimmer 0-100%
5	Colour	000-255	Green dimmer 0-100%
6		000-255	Blue dimmer 0-100%
7	Section 3	000-255	Red dimmer 0-100%
8	Colour	000-255	Green dimmer 0-100%
9		000-255	Blue dimmer 0-100%
10	Section 4	000-255	Red dimmer 0-100%
11	Colour	000-255	Green dimmer 0-100%
12		000-255	Blue dimmer 0-100%
13	Section 5	000-255	Red dimmer 0-100%
14	Colour	000-255	Green dimmer 0-100%
15		000-255	Blue dimmer 0-100%
16	Section 6	000-255	Red dimmer 0-100%
17	Colour	000-255	Green dimmer 0-100%
18		000-255	Blue dimmer 0-100%
19	Section 7	000-255	Red dimmer 0-100%
20	Colour	000-255	Green dimmer 0-100%
21		000-255	Blue dimmer 0-100%
22	Section 8	000-255	Red dimmer 0-100%
23	Colour	000-255	Green dimmer 0-100%
24		000-255	Blue dimmer 0-100%



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM